

METHOD OF MAKING NiFeCo-O-N OR NiFeCo-N FILMS FOR SHIELDS AND/OR POLES OF A MAGNETIC HEAD

5

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a method of making NiFeCo-O-N or NiFeCo-N films for shields and/or poles of a magnetic head and, more particularly, to a method of employing unique process conditions in a DC magnetron for forming such films.

10

2. Description of the Related Art

15

The heart of a computer is an assembly that is referred to as a magnetic disk drive. The magnetic disk drive includes a rotating magnetic disk with write and read heads that are suspended by a suspension arm above the rotating disk. An actuator swings the suspension arm, placing the write and read heads over selected circular tracks on the rotating disk. The write and read heads are directly mounted on a slider that has an air bearing surface (ABS). The suspension arm biases the slider into contact with the surface of the disk when the disk is not rotating. When the disk rotates, air is swirled by the rotating disk adjacent the ABS of the slider, causing the slider to ride on an air bearing a slight distance from the surface of the rotating disk.

20

When the slider rides on the air bearing, the write and read heads are employed for writing magnetic impressions to and reading magnetic impressions from the rotating disk. The read and write heads are connected to processing circuitry that operates according to a computer program to implement the writing and reading functions.

25

The write head includes a coil layer embedded in insulation layers (insulation stack) with the insulation stack being sandwiched between first and second pole piece layers (P1 and P2). A gap is formed between the first and second pole piece layers by a nonmagnetic gap layer at the air bearing surface (ABS) of the write head. The pole piece layers are connected at a back gap. Current conducted to the coil layer induces a magnetic field into the pole pieces that fringes across the gap between the pole pieces at the ABS. The fringe field writes information in tracks on moving media, such as in circular tracks on a rotating disk.

30

In recent read heads, a spin valve sensor is employed for sensing magnetic fields from the rotating magnetic disk. The sensor includes a nonmagnetic conductive layer, hereinafter referred to as a spacer layer, sandwiched between first and second ferromagnetic layers, hereinafter referred to as a pinned layer, and a free layer. First and second leads are connected to the spin valve sensor for conducting a sense current therethrough. The magnetization of the pinned layer is pinned perpendicular to an air bearing surface (ABS) of the head and the magnetic moment of the free layer is located parallel to the ABS but free to rotate in response to external magnetic fields. The magnetization of the pinned layer is typically pinned by exchange coupling with an antiferromagnetic layer. A spin valve sensor is sometimes referred to as a giant magnetoresistive (GMR) sensor. When a spin valve sensor employs a single pinned layer it is referred to as a simple spin valve sensor. In the read head the spin valve sensor is located between first and second read gap layers and the read gap layers are located between first and second shield layers (S1 and S2).

The shield layers (S1, S2) and pole piece layers (P1, P2) are in close proximity to the read sensor. Because of this proximity, it is important that the layers be magnetically stable. In order to achieve this, the shield or pole layers are formed by plating or sputter deposition in the presence of a magnetic field that is parallel to the ABS in the plane of the shield or pole layer. The field orients the easy axis (e.a.) of the shield or pole layer in the direction of the field, namely parallel to the ABS and in the plane of the shield or pole layer. This orientation also means that the magnetic domains in the shield or pole layer in the vicinity of the sensor are also aligned with their longitudinal axes parallel to the ABS in the plane of the shield or pole layer. It is important that these domains retain their orientation as formed and not move around when subjected to extraneous fields such as fields from the write head or fields from the rotating magnetic disk. When these magnetic domains move, noise is generated which is referred to in the art as Barkhausen noise. This noise seriously degrades the read signal of the read head. Further, if the magnetic domains do not come back to their original position, the shield or pole layer exerts a differently oriented field on the free layer of the spin valve sensor. This changes the magnetic bias on the free layer causing read signal asymmetry.

There are numerous materials which may be used in the construction of shield layers (S1 and S2) and pole piece layers (P1 and P2), the most common being NiFe. Nickel iron (NiFe), with a composition typically of approximately $\text{Ni}_{81}\text{Fe}_{19}$ (wt.%), is a soft magnetic material that provides good shielding of the spin valve sensor from magnetic fields except within the read gap where signals are sensed by the sensor. Nickel iron (NiFe) also has near zero magnetostriction so that after lapping the head to form the ABS there is near zero stress induced anisotropy. Unfortunately, however, nickel iron (NiFe) has a low intrinsic magnetic anisotropy (H_K). Intrinsic magnetic anisotropy is the amount of applied field required to rotate the magnetic moment of the layer 90 degrees from an easy axis orientation. The intrinsic magnetic anisotropy of nickel iron (NiFe) is 2-5 oersteds (Oe). After the first shield layer (S1) and second shield layer (S2) layer are formed, they are subjected to unfavorable magnetic fields that are required in subsequent processing steps. The insulation layers of the insulation stack, which are typically photoresist layers, are hard bake annealed in the presence of a magnetic field which is directed perpendicular to the ABS for the purpose of maintaining the magnetic spins of the antiferromagnetic pinning layer in the spin valve sensor oriented in a direction perpendicular to the ABS. The hard bake anneals are typically at least three high temperature anneals with each anneal typically being performed at around 232°C for 400 minutes. These annealing steps reduce the anisotropy field H_K of nickel iron (NiFe) to very low values of 0-1 Oe.

The field typically employed for maintaining the spins of the pinning layer during hard bake of the insulation stack is about 1500 Oe. Because of the low intrinsic magnetic anisotropy of a nickel iron (NiFe) shield layer, for instance, the aforementioned anneals in subsequent processing steps can cause the easy axis and the magnetic domains of the shield layer to switch their orientation such that they are no longer parallel to the ABS. The magnetic field present in these anneals reduces or destroys the intrinsic anisotropy field that was created in the nickel iron (NiFe) when it was originally formed and may create an anisotropy field perpendicular to the ABS. This is a very unfavorable orientation for magnetic domains of a shield layer. When the shields are subjected to perpendicular fields from the write head during the write

function or subjected to perpendicular fields from the rotating magnetic disk the magnetic domains will move. This causes Barkhausen noise which degrades the read signal and causes a potential change in biasing of the spin valve sensor which results in read signal asymmetry.

5 Some shield materials such as Sendust that require high temperature (475°C) annealing on the easy axis can withstand subsequent hard axis annealing at 230-270°C. Others such as plated 80/20 NiFe or CoTaZr have been shown to be stabilized to some degree by an initial anneal on the easy axis at a higher temperature, such as 280°C, than will be encountered during later processing. This strategy may
10 be workable for S1, which is formed before the GMR sensor, but not for S2, which must be made after the GMR sensor has been deposited. Annealing on the easy axis is not acceptable for many exchange materials employed in GMR sensors. Other materials considered for write head and shield materials, such as FeN, FeAlN, FeTa₂N, FeZrN, FeRuN and CoTaZr reduce or even switch H_K in conventional processing.

15 In general, it is desirable to minimize the reduction of H_K that occurs in hard axis annealing, and it is particularly desirable that this be done while simultaneously achieving low hard axis coercivity, H_{CH} , and near zero magnetostriction λ for the process conditions used for the GMR wafers. Accordingly, there is a strong-felt need for a material for the first shield layer (S1), the second shield (S2) and first and
20 second pole piece layers (P1 and P2) that will remain sufficiently stable after being subjected to heat and magnetic fields employed in subsequent process steps without pre-annealing along the easy axis.

SUMMARY OF THE INVENTION

25 I employ NiFeCo alloys (approximately $(\text{Ni}_{0.81}\text{Fe}_{0.19})_{100-x}\text{Co}_x$ (wt%), where $0.5 < x < 25$) for increasing H_K . These alloys have H_K in the range of 5-25 Oe as-deposited or after easy axis annealing. It has been found, however, that NiFeCo films sputtered under a variety of conditions all lose anisotropy, and in some cases switch their easy axis direction, when subjected to the hard axis annealing conditions in the
30 present hard bake anneal process (232°C, 400 min). In addition, thick sputtered NiFeCo films (1-2 μm), even those with near-zero magnetostriction, have vertical

anisotropy. It is desirable to improve sputtered NiFeCo films so they possess high anisotropy, low coercivity, and in-plane anisotropy after GMR head processing.

I have found that doping NiFeCo with N₂O or N₂ greatly increases H_K after hard axis annealing and that when laminated with, for example, alumina or silica, thick structures can be sputter deposited with excellent in-plane anisotropy. Approximately 1.8 μm thick films were sputter deposited on Al₂O₃-TiC ceramic substrates with lapped undercoat alumina from a target with composition Ni_{73.2}Fe_{18.1}Co_{8.7} (wt%) in a Balzers Z660 sputtering system using DC magnetron at a power of 1750 W, gas pressure of 2.0 x 10⁻³ mbar, and no substrate bias. The gas was a mixture of Ar and either N₂O or N₂. After deposition, the films were annealed three times on the hard axis at 232°C for 400 min in a magnetic field of approximately 1500 Oe. A typical film after annealing had an H_K of 10.8 Oe with in-plane anisotropy.

An object of the present invention is to provide a method of making high uniaxial anisotropy H_K films after hard axis annealing.

Another object is to provide a method of making the foregoing films with low hard axis and easy axis coercivities and low magnetostriction.

A further object is to provide a method of making the foregoing films into unique laminations which are especially useful for second pole piece layers of a write head.

Other objects and attendant advantages of the invention will be appreciated upon reading the following description taken together with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a plan view of an exemplary magnetic disk drive;

Fig. 2 is an end view of a slider with a magnetic head of the disk drive as seen in plane 2-2;

Fig. 3 is an elevation view of the magnetic disk drive wherein multiple disks and magnetic heads are employed;

Fig. 4 is an isometric illustration of an exemplary suspension system for supporting the slider and magnetic head;

Fig. 5 is an ABS view of the magnetic head taken along plane 5-5 of Fig. 2;

Fig. 6 is a partial view of the slider and a piggyback magnetic head as seen in
5 plane 6-6 of Fig. 2;

Fig. 7 is a partial view of the slider and a merged magnetic head as seen in plane 7-7 of Fig. 2;

Fig. 8 is a partial ABS view of the slider taken along plane 8-8 of Fig. 6 to show the read and write elements of the piggyback magnetic head;

10 Fig. 9 is a partial ABS view of the slider taken along plane 9-9 of Fig. 7 to show the read and write elements of the merged magnetic head;

Fig. 10 is a view taken along plane 10-10 of Figs. 6 or 7 with all material above the coil layer and leads removed;

15 Fig. 11 is an isometric ABS illustration of a read head which employs a pinned spin valve (SV) sensor;

Fig. 12 is a schematic illustration of a DC magnetron sputtering system which may be employed in the present invention;

Fig. 13 is a view taken along plane 13-13 of Fig. 12;

20 Fig. 14 is a schematic cross-sectional illustration of various layers employed in Examples I-VI;

Fig. 15 is a schematic cross-sectional illustration of various layers employed in Examples VIII and IX;

Fig. 16 is a schematic cross-sectional illustration of various layers employed in Examples X-XII;

25 Fig. 17 is a schematic cross-sectional illustration of various layers employed in Example XIII;

Fig. 18 is a plot of various single layer films and laminated films made in a DC magnetron sputtering system with various percentages of N_2O in Ar and various total film thicknesses;

Fig. 19 is a plot of various single layer films and laminated films made in a DC magnetron sputtering system with a process gas having various percentages of N₂ in Ar and various total film thicknesses;

Fig. 20 is a B/H loop for Example I;

5 Fig. 21 is a B/H loop for Example II;

Fig. 22 is a B/H loop for Example V;

Fig. 23 is a B/H loop for Example XIV;

Fig. 24 is a B/H loop for Example XV;

10 Figs. 25A-25H are side views of portions of layers that are constructed in a merged MR head;

Fig. 26 is an elevation view of a portion of a merged MR head writing signals into a rotating magnetic disk;

Fig. 27 is the same as Fig. 19 except the disk is injecting magnetic signals into the magnetic head;

15 Figs. 28A-28C are plan views of the prior art shield or pole piece layer of the magnetic head with magnetic domains shown schematically in various conditions;

Figs. 29A-29D are plan views of a shield or pole piece layer of a magnetic head with magnetic domains shown schematically under various applied field conditions.

20

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Magnetic Disk Drive

Referring now to the drawings wherein like reference numerals designate like or similar parts throughout the several views, Figs. 1-3 illustrate a magnetic disk drive

25 30. The drive 30 includes a spindle 32 that supports and rotates a magnetic disk 34. The spindle 32 is rotated by a motor 36 that is controlled by a motor controller 38. A combined read and write magnetic head 40 is mounted on a slider 42 that is supported by a suspension 44 and actuator arm 46. A plurality of disks, sliders and suspensions may be employed in a large capacity direct access storage device (DASD) as shown

30 in Fig. 3. The suspension 44 and actuator arm 46 position the slider 42 so that the magnetic head 40 is in a transducing relationship with a surface of the magnetic disk

34. When the disk 34 is rotated by the motor 36 the slider is supported on a thin (typically, .05 μm) cushion of air (air bearing) between the surface of the disk 34 and the air bearing surface (ABS) 48. The magnetic head 40 may then be employed for writing information to multiple circular tracks on the surface of the disk 34, as well as
5 for reading information therefrom. Processing circuitry 50 exchanges signals, representing such information, with the head 40, provides motor drive signals for rotating the magnetic disk 34, and provides control signals for moving the slider to various tracks. In Fig. 4 the slider 42 is shown mounted to a suspension 44. The components described hereinabove may be mounted on a frame 54 of a housing 55,
10 as shown in Fig. 3.

Fig. 5 is an ABS view of the slider 42 and the magnetic head 40. The slider has a center rail 56 that supports the magnetic head 40, and side rails 58 and 60. The rails 56, 58 and 60 extend from a cross rail 62. With respect to rotation of the magnetic disk 34, the cross rail 62 is at a leading edge 64 of the slider and the
15 magnetic head 40 is at a trailing edge 66 of the slider.

Fig. 6 is a side cross-sectional elevation view of a piggyback magnetic head 40, which includes a write head portion 70 and a read head portion 72, the read head portion employing an AP pinned spin valve sensor 74. Fig. 8 is an ABS view of Fig. 6. The spin valve sensor 74 is sandwiched between nonmagnetic electrically
20 insulative first and second read gap layers 76 and 78, and the read gap layers are sandwiched between ferromagnetic first and second shield layers 80 and 82. In response to external magnetic fields, the resistance of the spin valve sensor 74 changes. A sense current I_s conducted through the sensor causes these resistance changes to be manifested as potential changes. These potential changes are then
25 processed as readback signals by the processing circuitry 50 shown in Fig. 3.

The write head portion 70 of the magnetic head 40 includes a coil layer 84 sandwiched between first and second insulation layers 86 and 88. A third insulation layer 90 may be employed for planarizing the head to eliminate ripples in the second insulation layer caused by the coil layer 84. The first, second and third insulation
30 layers are referred to in the art as an "insulation stack". The coil layer 84 and the first, second and third insulation layers 86, 88 and 90 are sandwiched between first

and second pole piece layers 92 and 94. The first and second pole piece layers 92 and 94 are magnetically coupled at a back gap 96 and have first and second pole tips 98 and 100 which are separated by a write gap layer 102 at the ABS. An insulation layer 103 is located between the second shield layer 82 and the first pole piece layer 92.

5 Since the second shield layer 82 and the first pole piece layer 92 are separate layers this head is known as a piggyback head. As shown in Figs. 2 and 4, first and second solder connections 104 and 106 connect leads from the spin valve sensor 74 to leads 112 and 114 on the suspension 44, and third and fourth solder connections 116 and 118 connect leads 120 and 122 from the coil 84 (see Fig. 10) to leads 124 and 126 on

10 the suspension.

Figs. 7 and 9 are the same as Figs. 6 and 8 except the second shield layer 82 and the first pole piece layer 92 are a common layer. This type of head is known as a merged magnetic head. The insulation layer 103 of the piggyback head in Figs. 6 and 8 is omitted.

15 Fig. 11 is an isometric ABS illustration of the read head 72 shown in Figs. 6 or 7. The read head 72 has a spin valve sensor 130 which is located on an antiferromagnetic (AFM) pinning layer 132. The spin valve 130 has an antiferromagnetic (AFM) pinned layer 131 that has a magnetic moment pinned by the magnetic spins of the pinning layer 132 in a direction perpendicular to the ABS, such

20 as into the paper as shown by \otimes . The AFM pinning layer may be 425 Å of nickel oxide (NiO). First and second hard bias and lead layers 134 and 136 are connected to first and second side edges 138 and 140 of the spin valve sensor. This connection is known in the art as a contiguous junction and is fully described in commonly assigned U. S. Patent 5,018,037 which is incorporated by reference herein. The first

25 hard bias and lead layer 134 includes a first hard bias layer 140 and a first lead layer 142 and the second hard bias and lead layer 136 includes a hard bias layer 144 and a lead layer 146. The hard bias layers 140 and 144 produce magnetic fields that extend longitudinally through the spin valve sensor 130 for stabilizing its magnetic domains. The AFM pinning layer 132, the spin valve sensor 130 and the first and second hard

30 bias and lead layers 134 and 136 are located between nonmagnetic electrically insulative first and second gap layers 148 and 150. The first and second gap layers

148 and 150 are, in turn, located between a first shield layer (S1) 152 and a second shield first pole piece (S2) layer 154 (as shown in the piggyback head configuration of Fig. 6). The second shield layer may also be the first pole piece layer (S2/P1) in a merged head (as shown in the merged head configuration of Fig. 7).

5 As can be seen from Figs. 8-11 the ferromagnetic layers S1, S2, P1, P2 and S2/P1 have easy axes (ea) which are oriented parallel to the ABS and parallel to the surface planes of the layers. As shown in Fig. 11 the sensor 130 has a free layer 160 with its magnetic moment 162 oriented parallel to the ABS and a pinned layer 164 which has a magnetic moment 166 pinned perpendicular to the ABS, either toward or
10 away from the ABS, by the magnetic spins of the pinning layer 132. During the making of the read head hard axis annealing (high temperature in the presence of a field along the hard axis of the ferromagnetic layers S1, S2, P1 and P2) to preserve the exchange coupling field between the pinning layer 132 and the pinned layer 164 seriously degrades the magnetic anisotropy of these ferromagnetic layers when
15 formed according to prior art processes. This renders the read head inoperative.

The Invention

I have found that films constructed from NiFeCo-N or NiFeCo-O-N, hereafter designated as NiFeCo[-O]-N, have improved resistance to hard axis annealing. The
20 NiFeCo[-O]-N films of the present invention can be made to retain magnetic anisotropy after hard axis annealing and have stable domain structures. The NiFeCo[-O]-N films are ideal for shield layers (S1, S2), pole layers (P1, P2), combined second shield/pole layer (S2/P1), bilayer P1 and yoke applications due to higher H_K and lower hard axis coercivity H_{CH} after hard axis annealing.

25 I have found that using N_2O as the vehicle for delivering oxygen to the oxygen-containing films is very beneficial from the standpoint of process control. In the prior art, O_2 is used to provide oxygen. The difficulty with O_2 is that it reacts with the target and metal coating in the deposition system. This reaction removes O_2 from the process gas. The amount of oxygen available for reaction with the film therefore
30 depends on the prior condition of the entire chamber. Thus, reactive processes with oxygen are notoriously sensitive and difficult to control. I have found that using N_2O

as the reactive gas avoids this problem since it does not react with the bare metal surfaces in the chamber. In my work, the process has been very repeatable, and has exhibited none of the hysteretic behavior that is typical of processes with O₂. Using N₂O with Ar rather than O₂ with Ar as the reactive gas produces stable process behavior. This stability is a major advantage for a manufacturing process.

An exemplary direct current (DC) sputtering system 200 employed in the present invention is illustrated in Figs. 12 and 13. As shown in Fig 12 the system includes a sputtering chamber 202, first and second cathode targets 204 and 206 within the sputtering chamber, a plurality of wafer substrates 208 in the chamber where the ferromagnetic layers are to be formed, first and second magnetron cathode assemblies 210 and 212 with the targets 204 and 206 located between the magnetron arrays (not shown) inside the cathode assemblies and the wafer substrates 208, and a DC power supply 214 for applying DC power to the magnetron cathode assemblies 210 or 212. The wafer substrates 208 are electrically connected to a conductive turntable 222 which is rotated continuously under the targets by a conductive shaft 224. An RF power supply and matching network 226 optionally supplies a substrate bias to the wafer substrates 208 via the shaft 224 and the turntable 222. As shown in Fig. 13, rows and columns 230 of read write magnetic heads may be fabricated on each wafer substrate 208. An argon (Ar) supply 232 and a nitrogen (N₂) or nitrous oxide (N₂O) supply 234 are connected to the sputtering chamber via mass flow controllers for introducing precisely controlled flows of argon and nitrogen or nitrous oxide gases into the chamber. Before introducing these gases the chamber is pumped to high vacuum by a vacuum pump system 236. Thereafter, mass flow controllers 238 and 240 control the flows of the gases to produce a selected mixture of the gases in the chamber. A selected pressure is maintained by the flow of gas into the chamber and evacuation of the gas from the chamber through a vacuum line 242 between the chamber and the vacuum pump system 236. Optionally, the vacuum line 242 may have an adjustable valve (not shown) for adjusting pressure. In the following examples, the turntable 222 is continuously rotated during sputter deposition.

Examples I – VI

Examples I-VI are shown in Chart A hereinbelow wherein Chart A details magnetic properties of selected NiFeCo based laminates approximately 1.8 μm thick after hard axis annealing. In each of Examples I-VI a DC magnetron sputtering system, as shown in Figs. 12 and 13, was employed with a $\text{Ni}_{73.2}\text{Fe}_{18.1}\text{Co}_{8.7}$ (wt %) target. The process gases were Ar, N_2O and Ar, or N_2 and Ar. Power was 1750W and the pressure was 2.0×10^{-3} mbar. The substrate bias was zero. The substrate was Al_2O_3 -TiC ceramic with lapped alumina undercoat. The film structure was a lamination of four films of the magnetic films with thin interlayers of 25 \AA SiO_2 or 18 \AA alumina. The film structures were annealed three times in an oven at 232°C for 400 minutes along the hard axis. The easy axis of the films was established by employing the field from the magnets in the DC magnetron wherein each easy axis is in the plane of the film (major plane as contrasted to edge and side planes) and parallel to the ABS for a shield or pole piece of a magnetic head. The aforementioned hard axis is perpendicular to the aforementioned easy axis. Chart A shows for each example the film structure, the process gas, the uniaxial anisotropy H_K , the hard axis coercivity H_{CH} , the easy axis coercivity H_{CE} , the magnetostriction λ and anisotropy type, which is either vertical or in-plane. Vertical anisotropy is extremely undesirable for shields and poles in magnetic recording heads. The laminated structure in Example II with 3.2% N_2O in Ar has excellent soft in-plane properties and near zero magnetostriction after multiple hard axis anneals. The films in Examples I and III with no N_2O and 4.8% N_2O have high coercivities and vertical anisotropy. Thus, with properly selected conditions of pressure and substrate bias (none in this case), introduction of a prescribed amount of N_2O dramatically improves the film properties.

Fig. 14 is a schematic illustration of film structures 300 for Examples I-VI, which includes four magnetic films 302, 304, 306 and 308, which are 4500 \AA of NiFeCo-O-N or NiFeCo-N with amorphous interlayers 310, 312, 314, 316 and 318, which are 25 \AA of SiO_2 or 18 \AA of Al_2O_3 . The film structure is on a ceramic substrate 320 of Al_2O_3 -TiC and lapped alumina.

Fig. 18 is a plot of various percentages of N_2O in Ar as a process gas in the DC magnetron versus various total film thicknesses for single layer films and various laminated films wherein Examples I and II are shown along with other single layer films and various laminated films for comparison purposes. A plot is shown in Fig. 19 showing various percentages of N_2 in Ar as a process gas in the DC magnetron versus total film thicknesses of single layer films and various laminated films with Example V shown for comparison with other single layer films and various laminated films.

Fig. 20 is a B/H loop for Example I, Fig. 21 is a B/H loop for Example II and Fig. 22 is a B/H loop for Example V. The plots and the B/H loops are magnetic values before the aforementioned hard axis annealing. Before annealing Example I had vertical H_K and after annealing it still had vertical H_K . In Example II the film structure had in-plane H_K before annealing and in-plane H_K after annealing. From Fig. 20 it can be seen that the uniaxial anisotropy of Example I was 31.0 Oe before annealing and each of the hard axis and easy axis coercivities H_{CH} and H_{CE} were 7.60 Oe. From the B/H loop in Fig. 21 it can be seen that the uniaxial anisotropy H_K was 21.8 Oe, the hard axis coercivity H_{CH} was 0.25 Oe and the easy axis coercivity H_{CE} was 0.49 Oe. From Fig. 22 it can be seen that the uniaxial anisotropy H_K was 17.9 Oe, the hard axis coercivity H_{CH} was 0.20 Oe and the easy axis coercivity H_{CE} was 0.47 Oe. The high hard axis and easy axis coercivities H_{CH} and H_{CE} of Example I are undesirable while the low hard axis and easy axis coercivities H_{CH} and H_{CE} of Examples V and II are desirable.

It can be seen from Chart A that an optimized amount of process gas (N_2 or N_2O) can be employed for preventing vertical H_K in relatively thick laminates. This optimized amount of process gas can also prevent switching of in-plane H_K as seen in Examples II, IV, V and VI. It can be seen from Examples IV and V that the employment of SiO_2 or alumina interlayers makes little difference on the results. It can also be seen that N_2O produces a higher H_K than N_2 (Example II versus Example IV) with near zero magnetostriction and λ . The laminated structure in Example II is preferred with 3.2% N_2O in Ar since it has excellent soft in-plane properties and near zero magnetostriction after hard axis annealing. In contrast, Examples I and III with

no N₂O or 4.8% N₂O have high coercivities and vertical anisotropy. Accordingly, Chart A indicates that with properly selected conditions of pressure and no substrate bias that introduction of a prescribed amount of N₂O dramatically improves the film properties.

5

CHART A

Magnetic Properties of Selected NiFeCo-based Laminates Approximately 1.8 μm Thick After Hard Axis Annealing

Example	Film Structure	Process Gas	H _k (Oe)	H _{ch} (Oe)	H _{ce} (Oe)	λ ($\times 10^{-6}$)	Anisotropy Type
I	(25Å SiO ₂ /4500Å NiFeCo) _{4x} /25Å SiO ₂	Pure Ar	10.4	2.63	2.60	0.26	Vertical
II	(25Å SiO ₂ /4500Å NiFeCo-O-N) _{4x} /25Å SiO ₂	3.2% N ₂ O/Ar	10.8	0.09	0.56	0.07	In-plane
III	(25Å SiO ₂ /4500Å NiFeCo-O-N) _{4x} /25Å SiO ₂	4.8% N ₂ O/Ar	19.7	7.07	7.32	-0.73	Vertical
IV	(25Å SiO ₂ /4500Å NiFeCo-N) _{4x} /25Å SiO ₂	1.6% N ₂ /Ar	5.8	0.01	0.24	1.63	In-plane
V	18Å alumina/4500Å NiFeCo-N) _{4x} /25Å alumina	"	5.5	0.01	0.26	1.65	In-plane
VI	(25Å SiO ₂ /4500Å NiFeCo-O-N) _{4x} /25Å SiO ₂	1.6% N ₂ O/Ar	8.0	0.03	0.35	0.78	In-plane

Examples VII-XIII

Examples VII-XIII are shown in Chart B hereinbelow. A DC magnetron was employed with a Ni_{73.2}Fe_{18.1}Co_{8.7} (wt %) target and the process gas was Ar or N₂O in Ar. The power was 1750W and the pressure was 4.0×10^{-3} mbar. The substrate was Al-TiC ceramic with a lapped alumina undercoat and the examples were annealed three times in an oven at 232°C for 400 minutes on the hard axis. All of the film structures in Chart B had in-plane anisotropy. In Example VII the -3.7 for H_k indicates that the easy axis switched to the original hard axis direction during the hard axis annealing. Each of the films are 1500 Å thick for the film structures in Chart B whereas the films for the laminations in Chart A are each 4500 Å thick. The thinner films are more susceptible to anisotropy loss in hard axis annealing.

20

Chart B illustrates two methods in addition to reactive gas doping for making relatively thin NiFeCo films with good anisotropy, namely (1) depositing a NiFeCo-O-N seed layer with an optimized concentration of N₂O in the process gas prior to depositing the main NiFeCo-O-N layer with a separately optimized N₂O concentration, as shown in Examples X, XI and XII; and (2) using a SiO₂ underlayer, as shown in Example XIII.

Examples VIII and IX are shown by the film structure 350 in Fig. 15 which has a substrate 352 of Al₂O₃-TiC ceramic with lapped alumina. On the substrate is a 25 Å Al₂O₃ underlayer 354 and on the underlayer is a 1500 Å NiFeCo-O-N magnetic film 356. Example VII is the same as Example VIII except the magnetic film 356 is NiFeCo. Examples X, XI and XII are shown by the film structure 400 in Fig. 16 which has the same substrate 352 and underlayer 354, as shown in Fig. 15. On the underlayer 354 is a 90 Å NiFeCo-O-N seed layer 402 and on the seed layer is a 1410 Å NiFeCo-O-N magnetic film 404. Example XIII is shown by the film structure 450 in Fig. 17 which has the same substrate 352, as shown in Figs. 14 and 15. On the substrate is a 25 Å SiO₂ underlayer 452, on the underlayer is a 90 Å NiFeCo-O-N seed layer 454 and on the seed layer is a 1410 Å NiFeCo-O-N magnetic film 456.

CHART B
Magnetic Properties of Selected 1500Å NiFeCo-based Films
After Hard Axis Annealing

Example	Film Structure	Seed Layer Gas	Main Layer Gas	Sub. Bias (V)	H _k (Oe)	H _{ch} (Oe)	H _{ce} (Oe)	λ (x10 ⁻⁶)
VII	1500Å NiFeCo	No seed	Pure Ar	-50	-3.7	0.25	1.11	0.08
VIII	1500Å NiFeCo-O-N	No seed	2.4% N ₂ O/Ar	-50	2.6	0.49	0.98	-0.12
IX	1500Å NiFeCo-O-N	No seed	2.4% N ₂ O/Ar	None	3.2	0.54	1.01	-0.56
X	90Å NiFeCo-O-N/ 1410Å NiFeCo-O-N	2.4% N ₂ O/Ar	1.6% N ₂ O/Ar	None	3.3	0.58	0.97	0.11
XI	90Å NiFeCo-O-N/ 1410Å NiFeCo-O-N	4.0% N ₂ O/Ar	2.4% N ₂ O/Ar	None	3.5	0.55	0.98	-0.65
XII	90Å NiFeCo-O-N/ 1410Å NiFeCo-O-N	4.0% N ₂ O/Ar	1.6% N ₂ O/Ar	None	4.2	0.55	0.98	0.04
XIII	25Å SiO ₂ /90Å NiFeCo-O-N/ 1410Å NiFeCo-O-N	4.0% N ₂ O/Ar	1.6% N ₂ O/Ar	None	6.0	0.57	0.94	-0.21

A comparison of Examples VII and VIII shows that adding an optimal amount of N_2O (2.4% in this case) to the process gas prevents switching of the easy axis during hard axis annealing. Further increase in H_K (from 2.6 to 3.2 Oe) occurs when the substrate bias decreases from -50V to none (Example IX). Examples X, XII and XI illustrate the effect of introducing a 90 Å NiFeCo-O-N seed layer and then optimizing the N_2O separately for the seed layer and the main layer. Only small increases in H_K occur when the N_2O for the seed and main layers are changed alone (Examples X and XI). An optimal combination of N_2O for the seed and main layers (4.0% and 1.6%, respectively) results in an increase in H_K from 3.3 Oe (Example IX) to 4.7 Oe (Example XII). A significant further increase in H_K is obtained by using an SiO_2 underlayer to the NiFeCo-O-N seeded structure, as shown in Example XIII, where H_K is 6.0 Oe after hard axis annealing. Without the SiO_2 underlayer, the NiFeCo-O-N structure is deposited on a lapped alumina surface. Clearly, the nature of the amorphous underlayer plays a large role in the hard axis annealing resistance of these thin films.

Examples XIV-XV

Examples XIV and XV are shown in Figs. 18 and 23 respectively. Example XIV is a single layer film of NiFeCo-O-N which is about 1.8 μm thick and has vertical H_K . The process gas was 2.0% N_2O in Ar. The easy axis and hard axis loops are shown in Fig. 23 wherein H_K prior to annealing was 20.6 Oe, the hard axis coercivity H_{CH} was 4.19 Oe and the easy axis coercivity H_{CE} was 3.33 Oe. The vertical anisotropy and the high easy axis and hard axis coercivities are unacceptable.

Example XV is shown in Figs. 19 and 24. It can be seen from Fig. 19 that Example XV is a 1.8 μm thick single NiFeCo-N film, which has a desirable in-plane H_K . From Fig. 24 it can be seen that the H_K before annealing is 18.0 Oe, the hard axis coercivity H_{CH} was 0.34 Oe and the easy axis coercivity H_{CE} was 0.72 Oe. The hard axis and easy axis coercivities are low, which is desirable.

It can be seen in Fig. 18 that with a process gas having a N_2O content from 1.5% to 3.2% a single layer film of NiFeCo-O-N can be obtained with in-plane H_K up to approximately 0.6 μm . Fig. 18 also shows that laminated films of NiFeCo-O-N

4500 Å (0.45 μm) thick laminated four times can be produced with a total thickness of 1.8 μm with in-plane H_K . Fig. 19 shows that with a process gas having a range from 1% to 2% N_2 in Ar that single layer films of NiFeCo-N up to 1.8 μm can be fabricated with in-plane H_K .

5 Figs. 25A-25F illustrate the manufacture of the read head 472 with the NiFeCo[-O]-N shield layers with various processing temperatures and fields exerted on the first and second shield layers 552 and 554. In Fig. 25A, the first shield layer 552 is sputtered in the presence of a field 560 of about 50 Oe that is directed parallel to the ABS 562 and in the plane of the first shield layer 552. This causes the easy
10 axis 557 of the first shield layer 552 to be directed in the same direction, namely parallel to the ABS and parallel to the plane of the first shield layer 552. As shown in Fig. 25B, the first shield is then annealed at a temperature of about 270°C for 2 hours in the presence of a field of about 1,500 Oe that is directed parallel to the ABS in the plane of the first shield layer. As shown in Fig. 25C, after sputter depositing a
15 nonmagnetic electrically insulative first gap layer (G1) 548, a spin valve (SV) material layer 566 may be formed by sputtering in the presence of a field 568 that is directed perpendicular to the ABS 562. The field 568, which may be directed either to the right or to the left, is for the purpose of orienting the magnetic spins of the antiferromagnetic pinning layer 532 in Fig. 11 in a desired direction that pins the
20 magnetic moment of the pinned layer 531 in Fig. 11 in the same direction. After deposition, the structure is annealed at a high temperature, such as 220°C, in the presence of a magnetic field of 13000 Oe that is oriented perpendicular to the ABS (Fig. 25D). Unfortunately, the step shown in Fig. 25D may reposition the orientation of the magnetic domains of the first shield layer 552, which will be discussed in more
25 detail hereinafter. In Fig. 25E the spin valve layer 566 is photopatterned and milled to provide a spin valve sensor 530. In Fig. 25F, after sputter depositing a nonmagnetic insulative second gap layer 550, the second shield (S2 shown in Fig. 6) or second shield/first pole piece (S2/P1 in Fig. 7) layer 554 is formed by sputtering in the presence of a field 572 which is directed parallel to the ABS 562 and in the plane
30 of the S2/P1 layer, such as into the paper as shown by ⊗. This establishes the easy axis 558 of the second shield (S2) or second shield/first pole piece (S2/P1) layer 554

parallel to the ABS in the plane of the S2/P1 layer. This means that the magnetic domains of the second shield/first pole piece layer 554 will likewise be oriented parallel to the ABS.

Figs. 25G and 25H illustrate the manufacture of the write head 70 formed on top of read head 72 (as illustrated in Fig. 7 for a merged head). In Fig. 25G, various layers of the insulation stack 576 are hard baked at a high temperature, such as 232°C, in the presence of a field 578 of about 1500 Oe which is directed perpendicular to the ABS 562 for the purpose of maintaining the orientation of the magnetic spins of the pinning layer 532 in Fig. 11 directed perpendicular to the ABS. Unfortunately, this process may reorient the magnetic domains of the first and second shield layers 552 and 554, from their easy axis positions 557 and 558, which will be discussed in more detail hereinafter. In Fig. 25H, after completion of the magnetic head, the magnetic spins of the pinning layer 532 in Fig. 11 are reset by annealing at a high temperature of about 220°C in the presence of a field 580 of about 13,000 Oe which is again directed perpendicular to the ABS 562. Again, this processing step may reorient the magnetic domains of the shield layers from the easy axes 557 and 558, which will be described in more detail hereinafter. It should be noted that if the magnetic domains aligned along the easy axes 557 and 558 are moved from their aligned positions they will be magnetically unstable to signal fields from a rotating magnetic disk.

Fig. 26 shows magnetic flux fringing across the gap layer 502 of the write head portion of the magnetic head 540. This flux can move the magnetic domains of the first and second shield layers 552 and 554 to various positions if the magnetic domains are not aligned along the easy axes 557 and 558. In the same manner, as shown in Fig. 27, magnetic fields from the rotating magnetic disk 434 may move the magnetic domains of the first and second shield layers 552 and 554 if the magnetic domains are not aligned along the easy axes 557 and 558. If the magnetic domains of either of the layers 552 and 554 move around during operation of the head, this will cause what is known in the art as Barkhausen noise which seriously interferes with the read signal of the read head portion of the magnetic head.

Figs. 28A-28C show magnetic domain configurations for prior art material, such as NiFe, used for first and second shield layers. In Fig. 28A, a prior art first shield material is plated or sputter deposited in the presence of a field 602 which is directed parallel to the ABS 604 in the plane of the layer. This causes the magnetic domains, which are elongated diamonds, to align with their longitudinal axes parallel to the field 602 and with an easy axis 605. The shield layer is then subjected to annealing at a temperature of 270° C for 2 hours in the presence of a field of 1,500 Oe directed parallel to the ABS in the plane of the shield layer. In Fig. 28B, the first or second shield layer 600 is subjected to hard baking of the insulation layers of the write head in the presence of a field 578 perpendicular to the ABS, as shown in Fig. 25G, or subjected to annealing in the presence of a field 580 to orient the magnetic spins of the pinning layer 532 in Fig. 11. The annealing reduces the intrinsic magnetic anisotropy (H_K) of the first and/or second shield layers. In conjunction with an unfavorable stress induced anisotropy field, this can cause the magnetic domains to switch their positions from parallel to the ABS, as shown in Fig. 28A, to perpendicular to the ABS, as shown in Fig. 28B. Unfortunately, this is a very unstable position for magnetic domains when they encounter signal fields during the operation of the head. In Fig. 28C a write field, such as 200 Oe, or a disk field, such as 50 Oe, is applied to the first or second shield layer 600 which causes the magnetic domains to move from their position perpendicular to the ABS. This movement causes Barkhausen noise which is a problem obviated by the present invention. Accordingly, it is important that the intrinsic anisotropy (H_K) of the shield be higher so that even after annealing in a field perpendicular to the ABS, the shield retains sufficient anisotropy field (H_K). Alternatively, the shield material may become isotropic, thereby losing its intrinsic anisotropy (H_K).

Figs. 29A-29D illustrate plan views of a first or second shield layer 700 of the present invention wherein the magnetic domains are not destabilized by subsequent processing steps nor are they moved by applied fields during operation of the head. This is accomplished by employing a NiFeCo[-O]-N material processed according to the present invention.

In Fig. 29A the first and/or second shield layer 700 is constructed of the NiFeCo[-O]-N material. It may be sputter deposited in the presence of a field 702 which is parallel to the ABS 704 and the plane of the shield layer. This establishes the easy axis 705 parallel to the ABS and the longitudinal axes of the magnetic domains parallel to the ABS as shown. In the case of a first shield layer, it may also be annealed with the same field as described in reference to Fig. 25A. It is desirable that this orientation of the magnetic domains be retained during subsequent construction and operation of the head. In Fig. 29B the layer 700 has been subjected to hard baking and a field 578, as shown in Fig. 25G, or to annealing in the presence of a field 580 for resetting, as shown in Fig. 25H. Since the intrinsic anisotropy (H_K) of the NiFeCo[-O]-N material is higher, the shield can tolerate a greater loss of anisotropy during annealing and still retain sufficient intrinsic anisotropy to maintain the domains parallel to the ABS, even in the presence of possibly unfavorable stress induced anisotropy. In Fig. 29C, the layer 700 is subjected to applied fields from the write head or from the disk as shown in Figs. 26 and 27 which will cause the magnetic moments 706 to rotate, as shown. However, the magnetic domains retain their parallel orientation. Upon the removal of the operational applied fields 708 the magnetic moments 706 return to their parallel orientations, as shown in Fig. 29D. Accordingly, after construction of the first shield and/or second shield/first pole piece layer 700, as shown in Fig. 29A, the magnetic domains are not reoriented during the processing steps in Fig. 29B and do not move during operation of the head as shown in Fig. 29C. This results in the elimination of the aforementioned Barkhausen noise which degrades the performance of the read head.

Discussion

It can be seen from chart A that the best laminate structure is Example II where the process gas includes 3.2% N_2O . Example II has the highest in-plane H_K of all of the examples. From Chart B it can be seen that the best single layer film was constructed with a process gas of 1.6% of N_2O with an underlayer constructed with a process gas having 4.0% N_2O on an underlayer of SiO_2 . This film structure had an in-plane H_K of 6.0. Examples IV and V in Chart A show that a laminate film can be processed or constructed with a process gas of 1.6% N_2 with a resulting in-plane H_K

of 5.8 or 5.5. Fig. 18 shows that 4x laminated films can be constructed with a process gas containing 1.5% to 3.2% N_2O with a thickness of 1.8 μm with in-plane H_K . Fig. 19 shows that single layer films 1.8 μm thick can be constructed with a process gas in the range of 1% to 2% N_2 . Accordingly, the best structure is Example II with its high H_K of 10.8 Oe. Such a structure would be especially useful for the yoke portion of the second pole piece of the write head since the thinner (4500 Å) laminated layers have better domain structures for high frequency writing than thicker layers. However, the laminated structure is more difficult to fabricate because of the numerous layers. For this reason it is more practical to construct the first and/or shield layers of the read head of a single NiFeCo-N film, as shown in Fig. 19. A preferred shield layer or second shield/first pole piece common layer is preferably constructed with the aforementioned 1% to 2% N_2 in the process gas resulting in a 1.8 μm thick structure, as shown in Fig. 19. Optional shield, or combined shield and first pole structures, would be $(25\text{Å SiO}_2/4500\text{Å NiFeCo-O-N})_{4X}/2500\text{Å SiO}_2$ sputtered at 2.0×10^{-3} mbar in 3.2% N_2O/Ar process gas. Another option for the shields or combined second shield/first pole piece common layer is $(18\text{Å alumina}/4500\text{Å NiFeCo-N})_{4X}/2500\text{Å alumina}$ sputtered at 2.0×10^{-3} mbar and 1.6% N_2/Ar . An exemplary yoke structure is $(25\text{Å SiO}_2/90\text{Å NiFeCo-O-N}/1410\text{Å NiFeCo-O-N})_{16X}/25\text{Å SiO}_2$ which equals 2.44 μm sputtered at 4.0×10^{-3} mbar with 4.0% N_2O/Ar for a seed layer and 1.6% N_2O/Ar for a main layer of each NiFeCo-O-N laminate layer.

It can be seen from the above that the use of optimal amounts of N_2O or N_2 in the process gas in sputtering NiFeCo-O-N or NiFeCo-N films and laminates produces film structures that retain anisotropy after hard axis annealing. For thin layers a separately optimized NiFeCo-O-N seed layer and amorphous underlayer further increases H_K after hard axis annealing.

It should be understood with the NiFeCo material that the Co content can be adjusted to control the H_K . An increase in Co increases H_K . The magnetostriction λ can be controlled by adjusting the Fe content. NiFeCo has high thermal conductivity which is even higher than presently used Sendust. The only problem with NiFeCo is that when the film thickness is greater than about 4000 Å the film develops vertical anisotropy, which means that the magnetization at least partially is oriented out of the

plane of the film. This creates domains in the film which interfere with stable sensor operation. The aforementioned invention employs a particular process gas in a DC magnetron sputtering system under appropriate conditions for maintaining the desired in-plane anisotropy.

5 From Fig. 18 it can be seen that doping the process gas with less than 1.5% N₂O or greater than 3.2% N₂O may result in single film structures having a vertical H_K, and that doping with less than 1.6% or greater than 3.2% of N₂O for a laminated film may result in vertical H_K. Accordingly, there is a small range of doping with N₂O that is acceptable for producing films with in-plane H_K. The same is true for
10 Fig. 19 when N₂ is used for doping the process gas. Below 1% and above 2% may result in films having a vertical H_K so that a narrow range of 1% to 2% N₂ in a process gas is known to produce films with an in-plane H_K.

The preferred range for the various amounts of Ni, Fe and Co in the NiFeCo target of the magnetron sputtering system is (Ni_{0.80+x}Fe_{0.20-x})_{1-y}Co_y where -0.05 ≤ x
15 ≤ 0.05 and 0.00 ≤ y ≤ 0.15 (wt. fraction). A Co addition up to 0.15 (15%) still results in a soft magnetic film. It should be understood that the process gas may be doped with any nitrogen-containing gas other than N₂O or N₂, such as NH₃, NO₂, NO or NF₃. It should be understood that the DC magnetron is preferred to an RF magnetron. As mentioned hereinabove, the magnets of the DC magnetron may be employed for
20 orienting the easy axis of the sputtered films. Optionally, the sputter films can be located further away from the magnetron and magnets on the substrate may be employed for orienting the easy axis.

It should further be understood that the films in the laminated film may each be in a range from 500 Å to 2.0 μm with the interlayer being in a range from 5 Å to
25 100 Å. The range of thickness for the single layer may be 4500 Å to 3 μm. The interlayer material may be alumina, SiO₂, or other nonmagnetic material. The seed layers in each of examples X-XIII in Chart B may have a thickness range from 25 Å to 200 Å. It should be noted from Fig. 18 that a 4x laminated film structure is better than a 2x laminated film structure. It should be understood, however, that the number
30 of laminated magnetic films may be in a range from 2x to 30x.

Clearly, other embodiments and modifications of this invention will occur readily to those of ordinary skill in the art in view of these teachings. Therefore, this invention is to be limited only by the following claims, which include all such embodiments and modifications when viewed in conjunction with the above
5 specification and accompanying drawings.

I claim:

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210